

# *PRICE AND GESS*

ATTORNEYS AT LAW

2100 S.E. MAIN STREET, SUITE 250

IRVINE, CALIFORNIA 92614-6238

JOSEPH W. PRICE  
ALBIN H. GESS  
MICHAEL J. MOFFATT  
GORDON E. GRAY III  
BRADLEY D. BLANCHE  
J. RONALD RICHEBOURG

OF COUNSEL  
JAMES F. KIRK

A PROFESSIONAL CORPORATION  
TELEPHONE: (949) 261-8433  
FACSIMILE: (949) 261-9072  
FACSIMILE: (949) 261-1726

e-mail: pg@pgpatentlaw.com

## PATENT SPECIFICATION, CLAIMS & ABSTRACT

FILED 03-03-01

Inventor(s): ROGER F. BURLINGAME

Title: TWO AXIS OPEN LOOP GYROSCOPE

Attorney Docket No.: LIT3-BN17

EXPRESS MAIL LABEL NO. EL852656726US

DATE OF DEPOSIT: March 13, 2001

PATENT APPLICATION

# **TWO AXIS OPEN LOOP GYROSCOPE**

Roger F. Burlingame

# TWO AXIS OPEN LOOP GYROSCOPE

## BACKGROUND OF THE INVENTION

### 1. Field of the Invention

The present invention relates to gyroscopes, and in particular to an improved two-axis open loop "spinning mass" gyroscope capable of detecting angular input rates about two orthogonal axes without the use of slip rings.

### 2. Description of Related Art

Prior art gyroscopes that incorporate a gyroscopic element (flywheel) and a spin motor, typically incorporate piezoelectric crystals as pickoffs. When an angular motion is applied to the gyroscope the piezoelectric crystal is bent, which provides an electrical signal as a function of the bending. The electrical signal is then conducted through wires connected to the crystal and then through shaft-mounted slip rings for use by external circuitry. These prior art devices require added machining features, and additional mounting components, such as the slip rings. Great care must be exercised during the assembly process. Moreover, output signals from the piezoelectric crystal pickoffs are highly susceptible to slip ring contamination, thereby significantly reducing the life of the gyroscope because of the slip ring wear.

U.S Patent No. 4,715,227 discloses a gyroscope for detecting angular rates and linear accelerations by the use of a diamond-shaped piezoelectric crystal beam. This device suffers from the problems mentioned above when using piezoelectric crystals for pickoffs.

U.S Patent No. 5,156,056 discloses a gyroscope having two specifically restrained piezoelectric crystals aligned perpendicular to the spin axis. This prior art device has the same problems as discussed above. That is, the use of piezoelectric crystals requiring slip rings.

Therefore a need exists for an improved two-axis gyroscope capable of detecting angular input rates about two orthogonal axes without the use of slip rings.

### SUMMARY OF THE INVENTION

The present invention provides a simplified low-cost solution for applications requiring a two-axis gyroscope.

5 The present invention also provides an open loop device not requiring electro-magnetic devices that provide torque.

The present invention also provides an open loop device not requiring wire wound coils and magnets.

10 A feature of the present invention is the provision of a simplified two-axis open loop gyroscope that can be built from commercially available LED's and optical detectors as rotor pickoffs, thereby eliminating the need for wire wound AC-excited coils and laminated iron cores.

An advantage of the present invention is the reduced number of component parts required to construct the gyroscope.

15 Another advantage of the present invention is the simplification of the electronics necessary for its operation.

Yet another advantage of the present invention is that by eliminating magnetic torquers and pickoffs, specialized magnetic steels and their associated heat treats can be replaced with lower cost rotor and housing materials, such as stainless steel.

20 These and other features and advantages of the present invention, which will become apparent as the invention is described in detail below. The invention is a gyroscope having a rotor mounted onto a rotating shaft. The rotor has a circular flange extending from and perpendicular to one surface thereof. A suspension member having a flexible flange is affixed concentric with the rotating shaft and the rotor. A hysteresis synchronous electric drive motor is used for spinning the  
25 combined shaft with rotor. A light source is disposed on a stationary plate for emitting light perpendicular to a surface of the circular flange of the rotor. A light sensor is also disposed on the stationary plate and on a side of the circular flange opposite of the light source for producing an electrical signal as a function of the  
30 amount of light received. The light source and the light sensor are positioned such

that only a portion of the light from the source strikes the sensor when the gyro is in a quiescent rotating state. However, when the rotor is tilted as a function of an angular rotation rate applied to the gyroscope, the amount of light received by the sensor varies thereby producing an electrical signal indicative of the angular rotation rate.

5                Still other features and advantages of the present invention will become readily apparent to those skilled in the art from the following detailed description, wherein is shown and described only the preferred embodiment of the invention, simply by way of illustration of the best mode contemplated of carrying out the invention. As will be realized, the invention is capable of other and different  
10        embodiments, and its several details are capable of modifications in various obvious respects, all without departing from the invention. Accordingly, the drawings and description are to be regarded as illustrative in nature, and not as restrictive, and what is intended to be protected by Letters Patent is set forth in the appended claims. The present invention will become apparent when taken in conjunction with the following  
15        description and attached drawings, wherein like characters indicate like parts, and which drawings form a part of this application.

#### BRIEF DESCRIPTION OF THE DRAWINGS

The general purpose of this invention, as well as a preferred mode of use, its advantages and features will best be understood by reference to the following  
20        detailed description of an illustrative embodiment with reference to the accompanying drawings in which like reference numerals designate like parts throughout the figures thereof, and wherein:

Figure 1 illustrates a perspective view of the gyroscope of the present invention with a part cut away for viewing the interior thereof;

25                Figure 2 is a cross-sectional view of the gyroscope built in accordance with the present invention;

Figure 3A is a perspective view of the rotor built in accordance with the present invention;

30                Figure 3B is a perspective view of the suspension for holding the rotor to the main shaft;

Figure 4 is a perspective view of the optical pickoff stationary plate assembly;

Figure 5 is a cross-sectional detail showing mechanical operation of the present invention;

5 Figure 6 is a waveform diagram illustrating electrical operation of the present invention;

Figures 7A and 7B illustrate details of the flange, LED's and photo sensors; and

Figure 8 is a plot of reference pulses generated by the reference strobe.

10 DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

The following description is provided to enable any person skilled in the art to make and use the invention and sets forth the best modes contemplated by the inventors of carrying out his invention. Various modifications, however, will remain readily apparent to those skilled in the art, since the general principles of the present invention have been defined herein specifically to provide a two-axis, open loop, "spinning mass" gyroscope capable of detecting angular input.

Referring now to Figure 1, a perspective cut-away drawing illustrates the gyroscope built in accordance with the present invention. A shaft 10 has rotating freedom about a central or Z axis 11 and the shaft 10 rests on bearings 12. The shaft 10 is spun about the Z axis 11 by a synchronous hysteresis motor 13. Pressed onto an end of the shaft 10 opposite the motor 13 is a flexible suspension 15. The suspension 15 has a lower flange 15A with a slightly larger diameter than the top of the suspension. This lower flange 15A is press fitted inside the inner periphery of a rotor 16. Thus, the rotor 16 spins with the suspension 15 and is free to tilt from side to side, which will be elaborated upon hereinbelow.

Also shown in the cutaway view of Figure 1 is a stationary plate 17 having mounted thereon a plurality of light emitting diodes ("LED") 18 and an equal number of photo detectors 19, or light sensors. The plate 17 is stationary and does not rotate with the shaft 10 and rotor 16. Details of the plate 17 are shown in Figure 4 and will be amplified hereinbelow.

Referring now to Figure 2, a cross-section of the gyroscope according to the present invention is shown. Like reference numerals represent like components. The rotor 16 includes a lower ringed flange 16A, which is perpendicular to and concentric with the rotor for intercepting a part of the light emitted from the LED's 18.

5 As will be illustrated in Figure 5 and amplified hereinbelow, when the rotor 16 tilts, the amount of light passing from the LED's 18 to the detectors 19 will vary as a function of this tilt. The gyroscope is enclosed in a housing 20 and a base support 21.

Referring now to Figure 3A, the rotor 16 is illustrated with greater detail. The rotor 16 can be machined from mild steel. In this view, the rotor 16 is shown upside down in order to illustrate the flange 16A having a notch 35 formed therein. The notch 35 is used for generating a reference strobe, and will be explained further hereinafter. Threaded openings 22 are made in the rotor 16 for use in balancing the rotor 16. Referring now to Figure 3B, the suspension 15 is illustrated with greater detail. The suspension 15 includes a lower flange 15A, which forms two flexure blades

10 15 that define a torsional axis which provides the rotor 16 a rotational degree of freedom about an axis perpendicular to the shaft axis 11. The flange 16A can be cut using a wire Electrical Discharge Machining (or "EDM") process, which can erode conductive metals, by electrical spark discharges.

Referring now to Figure 4, the stationary plate 17 is shown with greater detail. The plate 17 includes a central opening 23, which is larger in diameter than the diameter of the shaft 10. The photo detectors 19, or sensors, are mounted on the periphery of the plate 17, and in the disclosed embodiment four such sensors are shown. Four LED's 18A, 18B, 18C, and 18D are mounted in axial alignment with each of the detectors 19A, 19B, 19C, and 19D, respectively; but, they are spaced a short distance

20 25 diametrically inward from the detectors. In particular, LED's 18A and 18B and concomitant detectors 19A and 19B are aligned on the X axis 24; and LED's 18C and 18D and concomitant detectors 19C and 19D are aligned on the Y axis 25. Note the gap between the LED 18A and the detector 19A, which gap is considerably wider than the thickness of the flange 16A so as to allow for any tilting movement of the rotor 16, as

30 will be explained hereinafter. Similar gaps are provided between the remaining LED's

and their concomitant detectors. In other embodiments of the invention a minimum of one LED and one optical detector are desired for both pickoff axes

Referring now to Figure 5, details of the relationship between the LED 18, photo detectors 19 and the rotor flange 16A are illustrated. In a quiescent state, i.e., the rotor 16 is spinning and no external rotation rates being applied to the gyroscope, light is transmitted from the LED 18 to the detector 19 as depicted by the arrows in Fig. 5. As a result of the proximity of the flange 16A, only a portion of the light from the LED 18 is received by the detector 19. In other words, part of the light from the LED 18 is shaded by the flange 16A as depicted by a rotor shadow mask 26 in Figure 5.

When an external rotational input rate is applied to the gyroscope, the rotor 16 tilts to a position 16' and the flange 16A tilts to a position 16A'. This allows more light to pass from the LED 18 to the detector 19, which change in light intensity is sensed as movement of the gyroscope. This will be illustrated in greater detail in Figure 6 and explained further hereinbelow.

As an example, Referring now to Figure 6, optical detector output waveforms from the gyroscope are shown during a constant angular input rate about the X-case gyro axis. As alluded to hereinabove with reference to Figure 5, a DC current to the LED 18 generates a constant source of emitted light that impinges upon the optical detector 19. The detector DC current output will vary with the amount of incident light. Angular motion of the gyroscope (including the rotor 16) due to a case input rate causes the rotor shadow mask 26 to vary the amount of illumination upon the optical detector 19. The result is a detector DC current output that is proportional to the case input rate. This DC current output is shown in Figure 6 as horizontal line 30. Waveform 31, or  $\theta$ , is the rotor motion during an applied case input rate, as seen by a shaft (rotating) fixed observer. The frequency of waveform 31 is the same as the shaft spin, or 1N. As an example, An input about the X-case axis causes a Y-case pickoff output signal (waveform 32), which includes a DC component plus a "2N" AC component. In addition, an X-case pickoff output signal (waveform 33) is a "2N" AC component that is phase shifted 90° from the Y-case pickoff AC component. From the foregoing and Figure 6, it can be appreciated that there are at least two possible methods for obtaining



a useful pickoff signal.

A first of these two methods is to measure the DC component of the output signal (i.e., the Y-pickoff for a X-case input rate and the X-pickoff for a Y-case input rate) while filtering and rejecting the 2N AC component. This method simplifies the pickoff processing electronics by eliminating the need for pickoff demodulation. This method requires a minimum of two optical pickoffs, one located along the X case axis and another along the Y case axis.

A second method for obtaining a useful pickoff signal requires only one pickoff, which can be located along either the X or the Y case axis. The AC output of the pickoff is proportional to angular input rate components of the X and Y case axes. This AC output from the pickoff is demodulated using both 2N SINE and 2N COSINE demodulation reference signals. A shaft speed detector may be used to generate the 2N SINE and 2N COSINE reference signals. The resulting two demodulated output signals, representing the angular input rate components of the gyro X and Y case axes, are filtered to obtain DC output components. These DC components are proportional to the gyro angular input rate components.

Referring now to Figure 7A, a detail of a portion of the rotor 16 with flange 16A, LED 18A and photo sensor 19A mounted on the stationary plate 17 is shown in a cut-away view. This drawing shows the shadow 26 on the photo sensor 18 caused by the flange 16A in a quiescent state. Figure 7B illustrates the same components, but with the reference notch 35 exposing all the light from the LED 18A onto the detector 19A.

Referring now to Figure 8, a timing diagram illustrates a reference strobe 36, which comprises a single pulse for each revolution of the rotor 16. This reference strobe 36 is used for generating sine and cosine reference waveforms, which is used in the demodulation process described hereinabove.

While the invention has been particularly shown and described with reference to a preferred embodiment, it will be understood by those skilled in the art that various changes in form and detail may be made therein without departing from the spirit and scope of the invention.

Those skilled in the art will appreciate that various adaptations and modifications of the just-described preferred embodiments can be configured without departing from the scope and spirit of the invention. Therefore, it is to be understood that within the scope of the appended claims, the invention may be practiced other than  
5 as specifically described herein.

100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000